



NT00C



NT00



NT0



NT1



NT2



NT3



NT4

## Application

NT low voltage H.R.C. fuse has features such/as light in weight, small in size, low in power loss and high in breaking capacity. This product has been widely used in overload and short circuit protection of electric installation. This product conforms to IEC60269 standards with all of the rating at the world advanced level.


## Specifications

Type	Rated current (A)	Fuse link			Fuse base		
		Rated voltage (V)	Rated power loss (W)	Weight (kg)	Type	Rated current (A)	Weight (kg)
NT00C	2	500, 600	0.41	0.15	Sist 101	160	0.2
	4		0.62				
	6		0.81				
	10		1.08				
	16		1.60				
	20		1.81				
	25		2.31				
	32		3.07				
	36		3.17				
	40		4.05				
	50		4.25				
	63		4.70				
	80		5.7				
	100		7				
NT00	4	500, 600	0.67	0.15	Sist 101	160	
	6		0.89				
	10		1.14				
	16		1.65				
	20		1.94				
	25		2.50				
	32		3.32				
	36		3.56				
	40		4.30				
	50		4.5				
	63		4.6				
	80		6				
	100		7.3				
	125		7.6				
NT0	160	500	9.6	0.2	Sist 160	160	0.32
	6	500, 600	1.03				
	10		1.42				
	16		2.45				
	20		2.36				
	25		2.7				
	32		3.74				
	35		4.3				
	40		4.7				
	50		5.5				
	63		6.9				
	80		7.6				
	100		8.9				
	125		10.1				
	160	500	15.2				

# NT Series

## Low Voltage Fuse


### Specifications



NT00 3P



Fuse Puller



NT2 3P

Type	Fuse link				Fuse base		
	Rated current (A)	Rated voltage (V)	Rated power loss (W)	Weight (kg)	Type	Rated current (A)	Weight (kg)
NT1	80	500, 600	0.41	0.36	Sist 201	250	0.8
	100		0.62				
	125		0.81				
	160		1.08				
	200		1.60				
	224		1.81				
	250		2.31				
NT2	125	500	3.07	0.15	Sist 401	400	1.2
	160		3.17				
	200		4.05				
	224	500, 600	4.25				
	250		4.70				
	300		5.7				
	315		7				
	355		0.67				
	400		15.2				
NT3	315	500, 600	21.7	0.85	Sist 601	630	1.5
	355		22.7				
	400		26.8				
	425		28.9				
	500	500	32				
	630		40.3				
NT4	800	380	62	1.95	Sist 1001	1000	3.45
	1000		75				