

## TJ-45 机电特性矩阵

### 刚度系数矩阵

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^E = \begin{pmatrix} 15.2 & 9.3 & 9.0 & 0 & 0 & 0 \\ 9.3 & 15.2 & 9.0 & 0 & 0 & 0 \\ 9.0 & 9.0 & 12.4 & 0 & 0 & 0 \\ 0 & 0 & 0 & 2.7 & 0 & 0 \\ 0 & 0 & 0 & 0 & 2.7 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.9 \end{pmatrix}^E 10^{10} N/m^2$$

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^D = \begin{pmatrix} 15.9 & 10.0 & 8.3 & 0 & 0 & 0 \\ 10.0 & 15.9 & 8.3 & 0 & 0 & 0 \\ 8.3 & 8.3 & 16.1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 5.3 & 0 & 0 \\ 0 & 0 & 0 & 0 & 5.3 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.9 \end{pmatrix}^D 10^{10} N/m^2$$

### 弹性柔顺系数矩阵

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^E = \begin{pmatrix} 12.9 & -4.1 & -6.4 & 0 & 0 & 0 \\ -4.1 & 12.9 & -6.4 & 0 & 0 & 0 \\ -6.4 & -6.4 & 17.4 & 0 & 0 & 0 \\ 0 & 0 & 0 & 36.9 & 0 & 0 \\ 0 & 0 & 0 & 0 & 36.9 & 0 \\ 0 & 0 & 0 & 0 & 0 & 34 \end{pmatrix}^E 10^{-12} m^2/N$$

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^D = \begin{pmatrix} 11.4 & -5.6 & -3.0 & 0 & 0 & 0 \\ -5.6 & 11.4 & -3.0 & 0 & 0 & 0 \\ -3.0 & -3.0 & 9.3 & 0 & 0 & 0 \\ 0 & 0 & 0 & 18.8 & 0 & 0 \\ 0 & 0 & 0 & 0 & 18.8 & 0 \\ 0 & 0 & 0 & 0 & 0 & 34 \end{pmatrix}^D 10^{-12} m^2/N$$

受夹介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^s = \begin{pmatrix} 750 & 0 & 0 \\ 0 & 750 & 0 \\ 0 & 0 & 680 \end{pmatrix}^s$$

自由介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^t = \begin{pmatrix} 1470 & 0 & 0 \\ 0 & 1470 & 0 \\ 0 & 0 & 1350 \end{pmatrix}^t$$

压电常数矩阵

$$\begin{pmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 485 & 0 \\ 0 & 0 & 0 & 485 & 0 & 0 \\ -131 & -131 & 310 & 0 & 0 & 0 \end{pmatrix} 10^{-12} C/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 37.3 & 0 \\ 0 & 0 & 0 & 37.3 & 0 & 0 \\ -11.0 & -11.0 & 26.0 & 0 & 0 & 0 \end{pmatrix} 10^{-3} Vm/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 13.1 & 0 \\ 0 & 0 & 0 & 13.1 & 0 & 0 \\ -4.2 & -4.2 & 14.9 & 0 & 0 & 0 \end{pmatrix} C/m^2$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 19.6 & 0 \\ 0 & 0 & 0 & 19.6 & 0 & 0 \\ -6.9 & -6.9 & 23.6 & 0 & 0 & 0 \end{pmatrix} 10^8 V/m$$