

TJ-46 机电特性矩阵

刚度系数矩阵

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^E = \begin{pmatrix} 17.5 & 12.6 & 10.6 & 0 & 0 & 0 \\ 12.6 & 17.5 & 10.6 & 0 & 0 & 0 \\ 10.6 & 10.6 & 11.3 & 0 & 0 & 0 \\ 0 & 0 & 0 & 2.6 & 0 & 0 \\ 0 & 0 & 0 & 0 & 2.6 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.5 \end{pmatrix}^E \cdot 10^{10} N/m^2$$

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^D = \begin{pmatrix} 17.5 & 12.5 & 10.6 & 0 & 0 & 0 \\ 12.5 & 17.5 & 10.6 & 0 & 0 & 0 \\ 10.6 & 10.6 & 15.9 & 0 & 0 & 0 \\ 0 & 0 & 0 & 5.4 & 0 & 0 \\ 0 & 0 & 0 & 0 & 5.4 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.5 \end{pmatrix}^D \cdot 10^{10} N/m^2$$

弹性柔顺系数矩阵

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^E = \begin{pmatrix} 15.0 & -5.1 & -9.3 & 0 & 0 & 0 \\ -5.1 & 15.0 & -9.3 & 0 & 0 & 0 \\ -9.3 & -9.3 & 26.3 & 0 & 0 & 0 \\ 0 & 0 & 0 & 38.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 38.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 40.2 \end{pmatrix}^E \cdot 10^{-12} m^2/N$$

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^D = \begin{pmatrix} 13.2 & -6.9 & -4.2 & 0 & 0 & 0 \\ -6.9 & 13.2 & -4.2 & 0 & 0 & 0 \\ -4.2 & -4.2 & 11.9 & 0 & 0 & 0 \\ 0 & 0 & 0 & 18.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 18.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 40.2 \end{pmatrix}^D \cdot 10^{-12} m^2/N$$

受夹介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^s = \begin{pmatrix} 735 & 0 & 0 \\ 0 & 735 & 0 \\ 0 & 0 & 675 \end{pmatrix}^s$$

自由介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^t = \begin{pmatrix} 1530 & 0 & 0 \\ 0 & 1530 & 0 \\ 0 & 0 & 1450 \end{pmatrix}^t$$

压电常数矩阵

$$\begin{pmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 520 & 0 \\ 0 & 0 & 0 & 520 & 0 & 0 \\ -153 & -153 & 430 & 0 & 0 & 0 \end{pmatrix} 10^{-12} C/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 38.4 & 0 \\ 0 & 0 & 0 & 38.4 & 0 & 0 \\ -11.9 & -11.9 & 33.5 & 0 & 0 & 0 \end{pmatrix} 10^{-3} Vm/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 13.5 & 0 \\ 0 & 0 & 0 & 13.5 & 0 & 0 \\ -0.5 & -0.5 & 16.2 & 0 & 0 & 0 \end{pmatrix} C/m^2$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 20.7 & 0 \\ 0 & 0 & 0 & 20.7 & 0 & 0 \\ -0.2 & -0.2 & 28.0 & 0 & 0 & 0 \end{pmatrix} 10^8 V/m$$