

TJ-47 机电特性矩阵

刚度系数矩阵

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^E = \begin{pmatrix} 15.6 & 8.9 & 8.8 & 0 & 0 & 0 \\ 8.9 & 15.6 & 8.8 & 0 & 0 & 0 \\ 8.8 & 8.8 & 13.2 & 0 & 0 & 0 \\ 0 & 0 & 0 & 3.1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 3.1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 3.4 \end{pmatrix}^E \cdot 10^{10} N/m^2$$

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^D = \begin{pmatrix} 15.8 & 9.1 & 7.8 & 0 & 0 & 0 \\ 9.1 & 15.8 & 7.8 & 0 & 0 & 0 \\ 7.8 & 7.8 & 17.8 & 0 & 0 & 0 \\ 0 & 0 & 0 & 5.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 5.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 3.4 \end{pmatrix}^D \cdot 10^{10} N/m^2$$

弹性柔顺系数矩阵

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^E = \begin{pmatrix} 11.4 & -3.5 & -5.3 & 0 & 0 & 0 \\ -3.5 & 11.4 & -5.3 & 0 & 0 & 0 \\ -5.3 & -5.3 & 14.7 & 0 & 0 & 0 \\ 0 & 0 & 0 & 32.3 & 0 & 0 \\ 0 & 0 & 0 & 0 & 32.3 & 0 \\ 0 & 0 & 0 & 0 & 0 & 29.8 \end{pmatrix}^E \cdot 10^{-12} m^2/N$$

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^D = \begin{pmatrix} 10.2 & -4.7 & -2.4 & 0 & 0 & 0 \\ -4.7 & 10.2 & -2.4 & 0 & 0 & 0 \\ -2.4 & -2.4 & 7.7 & 0 & 0 & 0 \\ 0 & 0 & 0 & 18.2 & 0 & 0 \\ 0 & 0 & 0 & 0 & 18.2 & 0 \\ 0 & 0 & 0 & 0 & 0 & 29.8 \end{pmatrix}^D \cdot 10^{-12} m^2/N$$

受夹介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^s = \begin{pmatrix} 960 & 0 & 0 \\ 0 & 960 & 0 \\ 0 & 0 & 870 \end{pmatrix}^s$$

自由介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^t = \begin{pmatrix} 1700 & 0 & 0 \\ 0 & 1700 & 0 \\ 0 & 0 & 1650 \end{pmatrix}^t$$

压电常数矩阵

$$\begin{pmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 460 & 0 \\ 0 & 0 & 0 & 460 & 0 & 0 \\ -135 & -135 & 320 & 0 & 0 & 0 \end{pmatrix} 10^{-12} C/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 30.6 & 0 \\ 0 & 0 & 0 & 30.6 & 0 & 0 \\ -9.2 & -9.2 & 21.9 & 0 & 0 & 0 \end{pmatrix} 10^{-3} Vm/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 14.3 & 0 \\ 0 & 0 & 0 & 14.3 & 0 & 0 \\ -4.9 & -4.9 & 18.5 & 0 & 0 & 0 \end{pmatrix} C/m^2$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 16.8 & 0 \\ 0 & 0 & 0 & 16.8 & 0 & 0 \\ -5.8 & -5.8 & 24.6 & 0 & 0 & 0 \end{pmatrix} 10^8 V/m$$