

TJ-50HD 机电特性矩阵

刚度系数矩阵

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^E = \begin{pmatrix} 15.2 & 10.2 & 10.0 & 0 & 0 & 0 \\ 10.2 & 15.2 & 10.0 & 0 & 0 & 0 \\ 10.0 & 10.0 & 12.7 & 0 & 0 & 0 \\ 0 & 0 & 0 & 2.1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 2.1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.5 \end{pmatrix}^E \cdot 10^{10} N/m^2$$

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^D = \begin{pmatrix} 15.6 & 10.7 & 9.3 & 0 & 0 & 0 \\ 10.7 & 15.6 & 9.3 & 0 & 0 & 0 \\ 9.3 & 9.3 & 16.1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 3.9 & 0 & 0 \\ 0 & 0 & 0 & 0 & 3.9 & 0 \\ 0 & 0 & 0 & 0 & 0 & 2.5 \end{pmatrix}^D \cdot 10^{10} N/m^2$$

弹性柔顺系数矩阵

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^E = \begin{pmatrix} 15.4 & -4.8 & -8.4 & 0 & 0 & 0 \\ -4.8 & 15.4 & -8.4 & 0 & 0 & 0 \\ -8.4 & -8.4 & 21.2 & 0 & 0 & 0 \\ 0 & 0 & 0 & 47.8 & 0 & 0 \\ 0 & 0 & 0 & 0 & 47.8 & 0 \\ 0 & 0 & 0 & 0 & 0 & 40.4 \end{pmatrix}^E \cdot 10^{-12} m^2/N$$

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^D = \begin{pmatrix} 13.3 & -6.9 & -3.7 & 0 & 0 & 0 \\ -6.9 & 13.3 & -3.7 & 0 & 0 & 0 \\ -3.7 & -3.7 & 10.5 & 0 & 0 & 0 \\ 0 & 0 & 0 & 25.7 & 0 & 0 \\ 0 & 0 & 0 & 0 & 25.7 & 0 \\ 0 & 0 & 0 & 0 & 0 & 40.4 \end{pmatrix}^D \cdot 10^{-12} m^2/N$$

受夹介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^s = \begin{pmatrix} 950 & 0 & 0 \\ 0 & 950 & 0 \\ 0 & 0 & 890 \end{pmatrix}^s$$

自由介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^T = \begin{pmatrix} 1780 & 0 & 0 \\ 0 & 1780 & 0 \\ 0 & 0 & 1950 \end{pmatrix}^T$$

压电常数矩阵

$$\begin{pmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 590 & 0 \\ 0 & 0 & 0 & 590 & 0 & 0 \\ -191 & -191 & 430 & 0 & 0 & 0 \end{pmatrix} 10^{-12} C/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 37.0 & 0 \\ 0 & 0 & 0 & 37.0 & 0 & 0 \\ -11.1 & -11.1 & 25.0 & 0 & 0 & 0 \end{pmatrix} 10^{-3} Vm/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 12.4 & 0 \\ 0 & 0 & 0 & 12.4 & 0 & 0 \\ -5.5 & -5.5 & 16.4 & 0 & 0 & 0 \end{pmatrix} C/m^2$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 14.4 & 0 \\ 0 & 0 & 0 & 14.4 & 0 & 0 \\ -5.9 & -5.9 & 19.6 & 0 & 0 & 0 \end{pmatrix} 10^8 V/m$$