

HB IP PBX 录音管理软件



1. 双击录音软件图标



2. 输入密码 “admin” ，点击登录打开软件

HB IP PBX 录音管理软件

HB国威录音管理系统

文件 帮助 退出

Status

连接状态  断开

服务器 192.168.100.3 5566

设备IP 0.0.0.0

设备号

Set

主叫号 部门 开始时间 2018-08-01

被叫号 姓名 结束时间 2018-08-02

启动接收 隐藏 录音路径

录音查询 播放录音 导出文件

E:\luyin

	主叫号	姓名	部门	被叫号	时长(S)	开始时间	结束时间	文件路径
▶ 1	8001			6688	12	2018-08-01 09:...	2018-08-01 09:...	E:\luyin\20180...
2	8001			6688	16	2018-08-01 09:...	2018-08-01 09:...	\20180801\8001...
*3								

软件打开后，因暂未与IP PBX对接，此时连接状态为 **断开**

此处服务器IP和端口号为安装录音软件的电脑IP和端口，将此信息填入IP PBX通话录音设置中

HB IP PBX 录音管理软件

The screenshot shows the software's configuration interface. At the top, there are tabs for '设备概况' (Device Overview), '网络配置' (Network Configuration), '语音配置' (Voice Configuration), '上网行为管理' (Internet Behavior Management), '对象管理' (Object Management), '网络安全' (Network Security), and '系统管理' (System Management). The '语音配置' tab is selected and circled in red. On the left sidebar, the menu items are: '快速向导' (Quick Guide), '用户管理' (User Management), '外线管理' (Outgoing Line Management), 'PBX业务' (PBX Business), '业务配置' (Business Configuration), '热线' (Hotline), '同组代答' (Group Answering), '彩铃' (Color Ring), '闹钟' (Alarm Clock), '快捷拨号' (Quick Dialing), '呼叫转移' (Call Forwarding), '黑名单' (Black List), '白名单' (White List), '话机登入登出' (Phone Login/Logout), '秘书业务' (Secretary Service), '一号通' (One Number), '语音邮箱' (Voice Mailbox), '企业总机' (Enterprise Main Switch), '话务台' (Operator Console), '队列' (Queue), '通话录音' (Call Recording), '计费设置' (Billing Settings), and '会议桥' (Conference Bridge). The 'PBX业务' and '通话录音' items are circled in red. The main content area is titled '语音配置>>PBX业务>>通话录音'. It contains two sub-tabs: '通话录音设置' (Call Recording Settings) and '通话录音号码' (Call Recording Numbers). The '通话录音设置' tab is active. Under the '录音设置' (Recording Settings) section, there is a checkbox labeled '对接录音服务器' (Connect to recording server) which is checked and circled in green with a '1'. Below it are two input fields: '录音服务器IP地址' (Recording server IP address) with the value '192.168.100.3' and '录音服务器端口' (Recording server port) with the value '5566'. These two fields are circled in green with a '2'. At the bottom right, there is an '应用' (Apply) button circled in green with a '3'. A red box with white text contains the instruction: '打开IP PBX 语音配置->PBX业务->通话录音菜单，启用录音服务器并填写录音服务器IP和端口号' (Open IP PBX Voice Configuration -> PBX Business -> Call Recording menu, enable recording server and fill in recording server IP and port number). Red arrows point from this box to the '语音配置' tab, the 'PBX业务' menu item, and the '通话录音' menu item.

设备概况 网络配置 **语音配置** 上网行为管理 对象管理 网络安全 系统管理 注销

快速向导
用户管理
外线管理
PBX业务
业务配置
热线
同组代答
彩铃
闹钟
快捷拨号
呼叫转移
黑名单
白名单
话机登入登出
秘书业务
一号通
语音邮箱
企业总机
话务台
队列
通话录音
计费设置
会议桥
PBX设置
状态报告

语音配置>>PBX业务>>通话录音

通话录音设置 通话录音号码

录音设置

☒ 对接录音服务器 ①

录音服务器IP地址 ② 192.168.100.3

录音服务器端口 5566

③ 应用

打开IP PBX 语音配置->PBX业务->通话录音菜单，启用录音服务器并填写录音服务器IP和端口号

HB IP PBX 录音管理软件

设备概览 网络配置 语音配置 上网行为管理 对象管理 网络安全 系统管理 注销

快速向导 用户管理 外线管理 PBX业务

- 业务前缀码
- 热线
- 同组代答
- 彩铃
- 闹钟
- 快捷拨号
- 呼叫转移
- 黑名单
- 白名单
- 话机登入登出
- 秘书业务
- 一号通
- 语音邮箱
- 企业总机
- 话务台
- 队列
- 通话录音
- 计费设置
- 会议桥

PBX设置 状态报告

语音配置>>PBX业务>>通话录音

通话录音设置 通话录音号码 ①

号码	姓名	用户组
☐ 6688	6688	Default
☐ 8001	8001	Default
☐ 6050	6050	Default
☐ 6060	6060	Default

4 1/1 << < 1 > >> 每页显示 10

删除 编辑 ②

录音号码管理

用户组 所有

待选分机

- 6001/6001
- 6002/6002
- 6003/6003
- 6004/6004
- 6005/6005
- 6006/6006
- 6007/6007
- 6008/6008
- 6009/6009
- 6010/6010
- 6011/6011
- 6012/6012
- 6013/6013
- 6014/6014
- 6016/6016
- 6017/6017
- 6018/6018
- 6019/6019
- 6020/6020
- 6023/6023
- 6024/6024
- 6025/6025

>> <<

已选分机 ③

- 6688/6688
- 8001/8001
- 6050/6050
- 6060/6060

确认 取消 ④

打开通话录音号码选项，启用需要录音的分机号码

HB IP PBX 录音管理软件

HB国威录音管理系统

文件 帮助 退出

Status

连接状态  正常

服务器 192.168.100.3 5566

设备IP 192.168.100.1:43905

设备号 600111405174230171

Set

主叫号 部门 开始时间 2018-08-01

被叫号 姓名 结束时间 2018-08-02

 隐藏 录音路径

 播放录音 导出文件

E:\luyin

	主叫号	姓名	部门	被叫号	时长(S)	开始时间	结束时间	文件路径
▶ 1	8001			6688	12	2018-08-01 09:...	2018-08-01 09:...	E:\luyin\20180...
2	8001			6688	16	2018-08-01 09:...	2018-08-01 09:...	\20180801\8001...
*3								

点击 启动接收，如
对接成功，连接状态
将显示 正常

HB IP PBX 录音管理软件



点击 试xx天 打开注册窗口



将步骤1中代码发送至深圳国威以获取步骤2注册码，注册成功后将获得永久使用权