

TJ-42 机电特性矩阵

刚度系数矩阵

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^E = \begin{pmatrix} 18.8 & 11.9 & 11.0 & 0 & 0 & 0 \\ 11.9 & 18.8 & 11.0 & 0 & 0 & 0 \\ 11.0 & 11.0 & 13.7 & 0 & 0 & 0 \\ 0 & 0 & 0 & 4.8 & 0 & 0 \\ 0 & 0 & 0 & 0 & 4.8 & 0 \\ 0 & 0 & 0 & 0 & 0 & 3.4 \end{pmatrix}^E \cdot 10^{10} N/m^2$$

$$\begin{pmatrix} C_{11} & C_{12} & C_{13} & 0 & 0 & 0 \\ C_{12} & C_{11} & C_{13} & 0 & 0 & 0 \\ C_{13} & C_{13} & C_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & C_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & C_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & C_{66} \end{pmatrix}^D = \begin{pmatrix} 18.8 & 11.9 & 10.8 & 0 & 0 & 0 \\ 11.9 & 18.8 & 10.8 & 0 & 0 & 0 \\ 10.8 & 10.8 & 17.5 & 0 & 0 & 0 \\ 0 & 0 & 0 & 8.5 & 0 & 0 \\ 0 & 0 & 0 & 0 & 8.5 & 0 \\ 0 & 0 & 0 & 0 & 0 & 3.4 \end{pmatrix}^D \cdot 10^{10} N/m^2$$

弹性柔顺系数矩阵

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^E = \begin{pmatrix} 11.1 & -3.4 & -6.2 & 0 & 0 & 0 \\ -3.4 & 11.1 & -6.2 & 0 & 0 & 0 \\ -6.2 & -6.2 & 17.3 & 0 & 0 & 0 \\ 0 & 0 & 0 & 20.8 & 0 & 0 \\ 0 & 0 & 0 & 0 & 20.8 & 0 \\ 0 & 0 & 0 & 0 & 0 & 29.0 \end{pmatrix}^E \cdot 10^{-12} m^2/N$$

$$\begin{pmatrix} S_{11} & S_{12} & S_{13} & 0 & 0 & 0 \\ S_{12} & S_{11} & S_{13} & 0 & 0 & 0 \\ S_{13} & S_{13} & S_{33} & 0 & 0 & 0 \\ 0 & 0 & 0 & S_{44} & 0 & 0 \\ 0 & 0 & 0 & 0 & S_{55} & 0 \\ 0 & 0 & 0 & 0 & 0 & S_{66} \end{pmatrix}^D = \begin{pmatrix} 10.1 & -4.4 & -3.5 & 0 & 0 & 0 \\ -4.4 & 10.1 & -3.5 & 0 & 0 & 0 \\ -3.5 & -3.5 & 10.0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 11.7 & 0 & 0 \\ 0 & 0 & 0 & 0 & 11.7 & 0 \\ 0 & 0 & 0 & 0 & 0 & 29.0 \end{pmatrix}^D \cdot 10^{-12} m^2/N$$

受夹介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^s = \begin{pmatrix} 590 & 0 & 0 \\ 0 & 590 & 0 \\ 0 & 0 & 430 \end{pmatrix}^s$$

自由介电常数矩阵

$$\begin{pmatrix} \varepsilon_{11} & 0 & 0 \\ 0 & \varepsilon_{11} & 0 \\ 0 & 0 & \varepsilon_{33} \end{pmatrix}^t = \begin{pmatrix} 1050 & 0 & 0 \\ 0 & 1050 & 0 \\ 0 & 0 & 750 \end{pmatrix}^t$$

压电常数矩阵

$$\begin{pmatrix} 0 & 0 & 0 & 0 & d_{15} & 0 \\ 0 & 0 & 0 & d_{24} & 0 & 0 \\ d_{31} & d_{31} & d_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 290 & 0 \\ 0 & 0 & 0 & 290 & 0 & 0 \\ -81 & -81 & 220 & 0 & 0 & 0 \end{pmatrix} 10^{-12} C/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & g_{15} & 0 \\ 0 & 0 & 0 & g_{24} & 0 & 0 \\ g_{31} & g_{31} & g_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 31.2 & 0 \\ 0 & 0 & 0 & 31.2 & 0 & 0 \\ -12.2 & -12.2 & 33.1 & 0 & 0 & 0 \end{pmatrix} 10^{-3} Vm/N$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & e_{15} & 0 \\ 0 & 0 & 0 & e_{24} & 0 & 0 \\ e_{31} & e_{31} & e_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 13.9 & 0 \\ 0 & 0 & 0 & 13.9 & 0 & 0 \\ -0.7 & -0.7 & 12.3 & 0 & 0 & 0 \end{pmatrix} C/m^2$$

$$\begin{pmatrix} 0 & 0 & 0 & 0 & h_{15} & 0 \\ 0 & 0 & 0 & h_{24} & 0 & 0 \\ h_{31} & h_{31} & h_{33} & 0 & 0 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 0 & 0 & 0 & 26.5 & 0 \\ 0 & 0 & 0 & 26.5 & 0 & 0 \\ -1.7 & -1.7 & 31.6 & 0 & 0 & 0 \end{pmatrix} 10^8 V/m$$